# **iHP1226**


iHP1200 SERIES 12-INCH, 120° x 60° LARGE FORMAT 2-WAY INSTALLATION LOUDSPEAKER

### SPECIFICATIONS

Loudspeaker Type: 2-way, full-range 50 Hz to 18 kHz Operating Range: 80 Hz to 16 kHz (±3 dB) Max Input Ratings 600W RMS, 1500W Program (Passive): 69 volts RMS, 155 volts momentary peak Max Input Ratings LF: 600W RMS, 1500W Program @ 8 ohms (Bi-amp): HF: 90W RMS, 180W Program @ 8 ohms Recommended Power 1200W to 1800W @ 8 ohms Amplifier (Passive): 101 dB SPL (63 Hz to 20 kHz 1/3 octave bands) Sensitivity (1W/1m): 102 dB SPL (250 Hz to 4 kHz speech range) Maximum Output: 129 dB SPL / 136 dB SPL (peak) Nominal Impedance: 8 ohms Minimum Impedance: 8 ohms @ 220 Hz Nominal Impedances LF: 8 ohms (Bi-amp): HF: 8 ohms Nominal -6dB 120° H (+14° / -38°, 2 kHz to 20 kHz) **Beamwidth:** 60° V (+14° / -20°, 2 kHz to 20 kHz) Axial Q / DI: 12.4 / 10.9, 2 kHz to 16 kHz Crossover Frequency: 1.5 kHz **Recommended Signal** 60 Hz 24 dB/Octave high pass filter Processing: Drivers: HF 1 x 2.8" VC/ 1.4" exit (2) NL4-compatible locking connectors Input Connection: (4) Terminal barrier strip Controls: Operating mode switch (bi-amp/passive) 13-ply solid birch plywood **Enclosure:** 30° total pitch angle Black paint finish, white paint finish, unfinished wood, portable option with built-in handles, and Finish / Options: multiple weather-resistant options for outdoor use. Contact factory for details. Mounting/Rigging (23) M10 flying/rigging inserts (4) M8 OmniMount™ 120 inserts Provisions: Grille: 16-gauge perforated steel, foam backed Required Accessories: Electronic high pass filter M10EYBLTKIT 10 mm eyebolt kit **Optional Accessories:** Mounting/rigging hardware for iHP1200 series Dimensions—Height: 30.42 inches (773 mm) Width (front): 16 inches (407 mm) Width (rear): 6.81 inches (173 mm) Depth: 18.26 inches (464 mm) Weight: 82 lbs (37.2 kg) Shipping Weight: 96 lbs (43.5 kg)

#### NOTES:

- Sensitivity: Free field pink noise measurement at 40 ft (12.2 m) at 20% power; extrapolated to 1 meter and an input of 2.83 volts RMS.
- 2. Watts: All wattage figures are calculated using the rated nominal impedance.



### **APPLICATIONS**

- · Theatre and auditoria
- · Houses of worship
- · Dance clubs, discotheques
- · Live sound reinforcement
- · Multipurpose sports facilities
- Stadiums
- · Audio visual

Shown: Standard Model iHP1226

### **FEATURES**

- 120° x 60° rotatable horn pattern
- · Large format waveguide delivers excellent pattern control
- 1.4" (36 mm) exit / 2.87" (72.2 mm) VC HF device
- 12" (300 mm) LF device
- · Passive and bi-amp operating modes
- (23) Load-rated M10 rigging points
- (4) M8 OmniMount™ 120 inserts
- Dual NL4-compatible locking connectors and barrier strip inputs
- Black, white, unfinished, portable and weather-resistant versions
- · Five-year warranty

#### **DESCRIPTION**

The iHP1226 is a premium quality, large format, full-range loudspeaker system. The driver complement consists of a 12" (300 mm) high power low frequency driver and a 1.4" (36 mm) exit / 2.87" (72.2 mm) edgewound voice coil compression driver. The large format rotatable horn flare delivers well controlled 120° x 60° dispersion, and utilizes high order crossovers to minimize band overlap. The well controlled off-axis response enhances system performance when combined with other iBOX Mid/Hi and subwoofer elements in clusters / arrays. The i112S and i212S subwoofer elements share the same cabinet profile and have been designed for integration with the iHP1226 for aesthetically pleasing clusters / arrays.

The iHP1226 can be used in both passive and bi-amp operating modes. The passive mode is designed to deliver outstanding performance without the use of a processor, while the bi-amp mode allows greater system flexibility. A compatible processor can be used to enhance the LF response, provide a crossover function for use with iBOX subwoofer elements, and much more. The solid birch plywood enclosure incorporates 23 load-rated M10 rigging points and 4 M8 OmniMount™ 120 inserts in the rear of the enclosure. Simple and flexible installation is achieved using optional hardware from an extensive range designed specifically for the iBOX series.


iHP1226 OPTIONS	
"W" suffix	White paint finish with white grille and hardware.
"U" suffix	Unfinished with black grille and hardware.
"H" suffix	Horizontal version with the HF horn rotated 90 degrees.
"P" suffix	<b>Portable</b> version with built-in handles, rubber feet and stacking cups on four recessed corner mounting points.
"WR" suffix	Weather-Resistant version with fiberglass-coated marine plywood, stainless steel fasteners and Weather-Stop™ grille. Available in grey, black and white finishes.

## 2-WAY INSTALLATION LOUDSPEAKER


### FREQUENCY RESPONSE

#### Resolution <500 Hz = 10 Hz, >500 Hz = 40 Hz, 1/8 octave smoothing 120 110 ᇟ 100 용 90 80 70 10 100 1,000 10,000 Frequency in Hertz


### **IMPEDANCE**




### **BEAMWIDTH**



### **AXIAL Q**



### DIMENSIONS



### ARCHITECTURAL SPECIFICATIONS

The loudspeaker system shall be a two-way, full-range bass reflex trapezoidal design with one 12 in. (300 mm) Cool-Coil™ LF driver and one 1.4 in. exit HF driver with a titanium diaphragm mounted to a 120° x 60° HF fiberglass horn. Drivers shall be connected to an integral crossover with a crossover frequency of 1.5 kHz. There shall be one four-terminal barrier strip and two NL4-compatible locking connectors. The terminal panel shall have a switch to select Bi-amp or Passive operating modes. The loudspeaker enclosure shall be 13-ply solid birch plywood and shall be fitted with 23 x M10 and 4 x M8 flying/rigging inserts and a painted finish. The front of the enclosure shall be fitted with a 16-gauge perforated steel grille backed with foam. The system shall have an amplitude response of 80 Hz to 16 kHz (+/- 3 dB), input capability of 69V RMS, 101 dB sensitivity at one meter and 2.83V / 8 ohms nominal impedance. The nominal dispersion shall be 120° H x 60° V from 2 kHz to 16 kHz. The loudspeaker shall be 30.42 in. (773 mm) H x 16.00 in. (407 mm) W (front) x 6.83 in. (173 mm) W (rear) x 18.26 in. (464 mm) D and weigh 82 lbs (37.2 kg).

Community strives to improve its products on a continual basis. Specifications are therefore subject to change without notice.



## iHP1200 Series

### **Portable Option**



Portable iBOX models include built-in Ergo-Grip handles, rubber feet and stacking cups on four recessed corner mounting points.

Order iHP1226P.


## **Weather-Resistant Option**



Weather-Resistant iBOX models feature fiberglass-coated marine plywood, 316 stainless steel fasteners, and three-layer Weather-Stop™ grille. Available in grey, black and white finishes. Specify passive or bi-amp mode at the time of ordering.

## **iHP1200 Series Mounting Accessories**

All Community iBOX mounting kits are specifically designed and engineered for the iBOX Series to provide a high degree of safety for supporting the loudspeaker cabinets. Available in black or white finishes to match the loudspeaker enclosure, bracket parts are made of black or white powdercoated steel. Hardware for attaching the bracket assembly kits to the enclosure are included. Each point is rated at 150 lbs working load limit (WLL) with a 15:1 safety ratio.



### IB-Y12 Horizontal Mounting Yoke

Standard "U" type mounting yoke bracket for iHP1200 Series loudspeakers, available in black and white finishes. Provides a yoke-type mounting with hardware for locking the aiming angle.




### IB-VY12 Vertical Mounting Yoke

Vertical mounting yoke for the iHP1200 Series loudspeakers. Each kit includes 2 compound angle plates that attach to the sides of the enclosure and a yoke bracket to fasten to these plates for vertically mounting the loudspeaker. Ideal for theatrical applications.



# IB-VTK Vari-Tilt Kit

Vari-tilt mounting kit for vertically flying two enclosures two-high at different horizontal and/or vertical aiming angles, with up to a 60° splay between cabinet-edge to cabinet-edge. Each kit includes one hang tab channel, two hang tabs, one turnbuckle and two turnbuckle brackets. A standard U-type mounting yoke (IB-Y12) must be purchased separately for each enclosure.




# IB-TPK Tight Pack Kit

Tight pack mounting kit for tight packing two same-size enclosures into a cluster. Each kit includes two tight pack plates, one spacer bracket and four M10 eyebolts. To tight pack three same-size enclosures, use two IB-TPK's; to tight pack four enclosures, use three IB-TPK's; etc. Use with same-size enclosures in

iHP1200 Series. A range extending to a 10° splay between cabinet edges is also possible using the tight pack

## iHP1200 Series Mounting Accessories (continued)



# IB-UPK Universal Planar Kit

Planar mounting kit for creating clusters of three same-size enclosures with up to a 45° splay between cabinetedge to cabinet-edge; or clusters of three different-size enclosures in "small-large-small" configuration with up to a 15° splay from cabinet-edge to cabinet-edge. Each kit includes one planar bracket, two planar angle plates and three M10 eyebolts.




### IB-VAK Vari-Angle Kit

Vari-angle hanging kit for vertically flying single enclosures at different aiming angles. Each kit includes one hang tab channel and two hang tabs. The hang tab channel mounts directly onto the top of the enclosure for an aesthetically pleasing installation. However, a standard horizontal mounting yoke may also be purchased separately for use with each enclosure at the installer's discretion.



Horizontal flying kit for horizontally array hanging two same-size enclosures with up to a 45° splay between cabinet-edge to cabinet-edge.

Note: When arraying four or more iHP1200 Series loudspeakers, a 0° and 5° splay is not possible. Each kit includes two lifting brackets, two planar spacer plates, two fly kit spacer brackets and four M10 eyebolts. To horizontally array three same-size enclosures, use two IB-HFK's; to horizontally array four same-size enclosures, use three IB-HFK's; etc. Use with same-size enclosures in the iHP1200 Series.



### IB-VFK Vertical Fly Kit

Vertical flying kit for vertically array hanging two same-size enclosures with up to a 45° splay between cabinet-edge to cabinet-edge. Note:

When arraying four or more iHP1200 Series loudspeakers, a 0° and 5° splay is not possible. Each kit includes one planar angle plate, one tight pack bracket, one fly kit spacer bracket and four M10 eyebolts. To vertically array

three same-size enclosures, use two IB-VFK's; to vertically array four same-size enclosures, use three IB-VFK's; etc. Use with same-size enclosures in the iHP1200 Series.



# M10EYBLTKIT 10mm Eyebolt Kit

Kit of four 10mm eyebolts for suspending and rigging iHP1200 Series loudspeakers, black zinc plated. Each iHP1200 loudspeaker features 23 M10 load-rated rigging points plus four (4) M8 OmniMount™ 120 series rear inserts.



### STKIT Seat Track Kit

Seat Track Kit for suspending a single loudspeaker enclosure. Each kit contains four seat track channels and both M10 (10mm) and 3/8-16" threaded fasteners for attachment to loudspeaker enclosures. Use M10 fasteners with all iHP1200 Series loudspeakers. Use multiple Seat Track Kits for multiple enclosures.

**CAUTION:** Installation of loudspeakers should only be performed by trained and qualified personnel. It is strongly recommended that a licensed and certified professional structural engineer approve the mounting design.

### WAIVER OF LIABILITY

Whenever Community Light and Sound, Inc. (CLS), dba Community Professional Loudspeakers is requested to provide advice or material regarding the design or installation of its equipment such advice or material is intended and provided for information purposes only. The advice or material is only intended to familiarize the user with various options for design, coverage and installation. User expressly agrees that CLS shall not be liable for any damages, whether in tort, contract, strict liability or otherwise consequential, incidental or otherwise to person or property as a result, directly or indirectly, of the use of any advice or material. The user of any advice or material provided by CLS assumes all risk and liability for the use thereof. Without limitation to the above, CLS does not accept liability or responsibility for the performance of any manufacturer, design, method, use, material or technique employed by the acoustic designer and/or installation company. All advice, information or material is subject to field variations and environmental conditions. All advice, information, or material given is offered on the assumption that common or standard practices for installation used in the construction trades is applied to all phases of the user's project. Actual assembly or configuration must be performed only by persons with knowledge of mechanical trades and rigging, where applicable. Any installation method must be certified by a Professional Engineer licensed in the state in which assembly or configuration is located.